

# LINSN TS952D LED Sending Box

## Sender box

### TS952

V1.2

Jan 2018

TS952 is a sender box with four network ports, and supports single, double and full color LED screen. It also supports 4K video source input and its maximum capability is 2.6 million pixels.

#### 1. Features:

- 1) One Audio signal input;
- 2) One DVI video signal input;
- 3) One HDMI video signal input;
- 4) Supports 4K video source input;
- 5) Supports RCG file read-back function;
- 6) Supports RCG file broadcasting function;
- 7) Supports CON file broadcasting function;
- 8) Supports 12bit/10bit/8bit video input;
- 9) Supports 16bit grey scale;
- 10) With four network output ports, supports common video source, like 2560x1024, 1920x1200, 2048x1152, etc;
- 11) Supported video format: RGB, YCrCb4:2:2, YCrCb4:4:4;
- 12) Supports cascade function;
- 13) Supports brightness auto-adjustment (requires light sensor).

#### 2. Appearance

#### Interface introduction

# LINSN TS952D LED Sending Box

- ① Power button/ indicator
- ② Power input: AC100~240V
- ③ Indicator: red for power; green for signal
- ④ 3.5mm audio input
- ⑤ USB connector for setup
- ⑥ HDMI signal input
- ⑦ DVI signal input
- ⑧ 4 gigabit network ports
- ⑨ UART-IN: cascade input
- ⑩ UART-OUT: cascade output
- ⑪ Light sensor connector for brightness auto-adjustment

### 3. Working conditions

Rated power consumption (W)	20
Working temperature (°C)	-20°C ~ 75°C
Working humidity (%)	0% ~ 95%
Weight (KG)	3

# LINSN TS952D LED Sending Box

**END**